



The Inovonics mobile duress pendant is designed to provide indoor room and floor level location with a button press. Inovonics mobile duress pendants only compatible with the EN7295 mobile duress gateway and EN5060 locators.

The location pendant is available in the following configurations:

Part #	Type	Buttons	Conditions
EN2224	Belt clip	Four	Fifteen
EN2233D	Necklace	Two	One
EN2233S	Necklace	One	One
EN2235D	Belt clip	Two	One
EN2235S	Belt clip	One	One
EN2236D	Belt clip	Two	Three
EN2238D	Belt clip	Two	Two

Product Features

Provides precise location for alarm events when used with Inovonics locators¹

LED flashes with all transmissions, ensuring operation at a glance

24/7 monitoring to maintain system health

Works with existing security system, eliminating forklift upgrades

Product Specifications

Dimensions:	3.0" x 1.6" x 0.72" (7.6 cm x 4 cm x 1.8 cm)
Weight:	1.6 oz (45 g) for necklace configuration; 2 oz (57 g) for belt clip configuration
Typical battery life:	Three years
Internal battery type:	Panasonic CR2 or equivalent
Accessories:	ACC603M metal necklace, ACC603P plastic necklace; ACC605-BK10 pendant black belt clip, ten pack
Operating environment:	
Temperature:	32 to 140°F (0 to 60°C)
Environment:	Non-condensing
Market:	North America
EchoStream® frequency:	902-928 MHz, frequency hopping spread spectrum
Compatible gateway:	EN7295 mobile duress gateway
Check in time:	3 minutes
Regulatory compliance:	FCC, RoHS, Industry Canada

Reference Materials (available at www.inovonics.com)

Mobile Duress Pendant Family Installation Instructions

User Manual Mobile Duress Application

- ¹ The location message is processed by a cloud application and can only be accessed through an active subscription to that service..
- The range and performance of any wireless product depends on the structure and environment in which it operates.
 - Continual enhancements to our products may cause specifications to change without notice.
 - Patents: 7,154,866; 7,554,932; 7,746,804; others pending.
 - Inovonics supports recycling and reuse whenever possible. Please recycle these parts using a certified electronics recycler.

Technical documents

For technical documents visit us at <http://www.inovonics.com/support/tech-documents/> or use the QR code below.

